

Installation Kit for frequency-control lifts WDGAK58B with shaft encoder



The following installation kits are available for fitting the encoder to a frequency controlled lift. Every installation kit consists:

1 x Encoder, 1 x Mountingangle, 1 x shielded cable 15 m length,
1 x double loop coupling, 5 x Shaftadapter

Mechanical Data

Housing

- Clamping flange: Aluminium
- Cap: die cast aluminum, powder coated
- Durchmesser: 58 mm

Shaft

- Material: stainless steel
- Diameter: 10 mm, H7
- Length: 20 mm
- Permitted load: max. 220 N radial
- Load: max. 120 N axial
- Starting torque: approx. 1 Ncm at ambient temperature

Bearings

- Type: 2 precision ball bearings
- Service life: 1x 10⁸ U revs. at 100 % shaft load
1x 10¹⁰ U revs. at 40 % shaft load
1x 10¹¹ revs. at 20 % shaft load

Max. operating speed: 8000 rpm

Weight: approx. 250 g

Connections: SH8: radial connector, 8 pin

Operating temperature: -20 °C up to +80 °C

Storage temperature: -30 °C up to +80 °C

Machinery Directive: basic data safety integrity level

MTTF_d: 200 a

Mission time (T_M): 25 a

Nominale service life 1×10^{11} revs. at 8000 rpm and

(L_{10h}): 20 % rated shaft load

Diagnostic coverage: 0 %

(DC)


Encoder-Order No.: WDG158B-10-YYYYY-ABN-M35-SH8

- YYYYY: with 1 up to 16384 PPR
- 6 channels, A, B, zero marker pulse N + Inv.
- 4.75 VDC up to 30 VDC HTL (TTL at 5 VDC)
with inv. output
- SH8: radial connector, 8 pin

YYYYY: Please specify required PPR.

Pin identification SH8:


Function	PIN
Positive	2
Negative	1
A	3
A inv.	6
B	4
B inv.	7
N	5
N inv.	8



The view of the soldered side of the connector connector corresponds to the view of the pin arrangement on the encoder.


- Complete retrofit set
- Quickly and reliably fitted with the aid of the accessories
- Cost-effective modernisation solution
- HTL output (TTL at 5 VDC)
- Threads: M8, M10, M12, M16 und M20

www.wachendorff-automation.com/wdgak58b



Mounting bracket:


The mounting bracket makes for easy installation of the encoder in the lift system. However care should be taken that the admissible load of the coupling is adhered to.



Order No.: MW58B

Cable:

The cable is 15 m in length and is shielded, however the shield is not connected to the connector housing at TTL/HTL. With a mated connector, the encoder meets protection class IP40.



The cable has a connection as follows:


Function	Colour
Positive	brown
Negative	white
A	green
A inv.	red
B	yellow
B inv.	black
N	gray
N inv.	violet
Shield:	cable braiding

Order No: KD84015

Double loop coupling:

The double loop coupling serves to compensate for any mis-alignment between the drive and the encoder. The coupling has extremely high compensation capabilities.

Features: excellent compensation capabilities
 Max. offset of shafts: axial: max. ± 4 mm
 radial: max. ± 3 mm
 angular: $\pm 12^\circ$
 Max. operating speed: 3000 rpm
 Starting torque: max. 200 Ncm
 Material:
 - Hub: zinc-plated
 - Compensating element: polyurethan
 Weight: 85 g
 Fixing: DIN 916 M4x6 (4x)
 Operating temperature: -30°C up to $+80^\circ\text{C}$




Order No.: DSK481010

Shaft adapters




Shaft adapters:

The shaft adapters are screwed into an appropriate thread on the lift and allow a simple connection via the double loop coupling.




Shaft adapter M8

Order No.: WDGWA10M08




Shaft adapter M10

Order No.: WDGWA10M10




Wellenadapter M12

Bestell-Nr.: WDGWA10M12



Shaft adapter M16

Order No.: WDGWA10M16



Shaft adapter M20

Order No.: WDGWA10M20

Note:

YYYY: Please specify required PPR.

Ordering information installation kit WDGA58B:

Description:	Order No.:
Installation kit comprising: - WDGI58B-10-YYYY-ABN-M35-SH8 - YYYY: with 1 PPR to 16.384 PPR 6 channels, A, B, N, A, B, N - M35: 4,75 VDC up to 30 VDC HTL with inv. output circuit (TTL at 5 VDC, RS422) - SH8: radial connector, 8 pin - MW58B: Mounting angle - KD84015: 15 m ready-made cable - DSK481010: Double loop coupling - Shaft adapter: 08, 10, 12, 16, 20	WDGA58BYYYYM35

Customs tariff number: 90318020

Country of origin: Germany

Montageanleitung Vollwellengeber WDG/WDGI,

Assembly instructions shaft encoder, Notice de montage codeur rotatif à arbre plein,
Instrucciones de montaje encoder ad albero pieno, istruzioni di montaggio encoders de eje saliente.



WDGI (Stecker, connector, connecteur, conector, spina):
-40 °C ... +85 °C (-40 °F ... +185 °F)
WDG* + WDGI** (Kabel, cable, Câble, Cable, cavo):
-20 °C ... +80 °C (-4 °F ... +176 °F)
Option: * -40 °C ... +80 °C (-40 °F ... +176 °F)
 ** -40 °C ... +85 °C (-40 °F ... +185 °F)
1Vss (1Vpp): -10 °C ... +70 °C (14 °F ... +158 °F)
58T: -10 °C ... +70 °C (58T: +14 °F ... +158 °F)



°C
(°F)



-30 °C...+80 °C
(-22 °F...+176 °F)




Montage nur qualifiziertes Personal, Assembly only qualified personnel,
Montage par qualifié personnel, Montaggio solo personale qualificato,
Montaje solamente personal cualificado


Sicherheitsmassnahmen/Safety instructions: Einsatz nur in Industrieumgebung und NICHT in sicherheitsrelevanten Bereich. Only for use in industrial environments and NOT for safety-relevant areas. Utilisation uniquement dans un environnement industriel et PAS dans un domaine lié à la sécurité. Utilízelo sólo en entornos industriales y NO en áreas relevantes para la seguridad. Utilizzare solo in ambienti industriali e NON in aree riguardanti la sicurezza.

Power supply:
Class 2/LPS only




DIN EN 100015-1






R1




R2

Kabel ø cable, Câble, Cable, cavo	R1	R2	Temperatur Temperature, Température, Temperatura, Temperatura
≤ 7 mm	31,5 mm	94,5 mm	T > -20 °C (-4 °F)
> 7 mm	41,5 mm	124,5 mm	T > -20 °C (-4 °F)
≤ 7 mm	46,5 mm	139,5 mm	T > -40 °C (-40 °F)
> 7 mm	62,3 mm	186,9 mm	T > -40 °C (-40 °F)


36C 58N
36K 58S
40K 58T
58B 58V
58D 63B
58K 70B




36A 58C
36J 58D
40A 58K
50B 58N
58A 58T
58B 63B




24C 58B
30A 58C
36A 58D
36C 58K
36J 58N
36K 58S
40A 58T
40K 58V
50B 63B
58A 70B




36S
40S
50V
53S
53V




58B
58D
58K
58N
58S
58T
58V



63Q
67Q
115T
115M




58A + MG58A




Gewinde (8.8)
Screw thread, Filet, Rosca, filetto

	Empfohlenes Anzugsdrehmoment Recommended starting torque Moment de rotation recommandé appliqué à l'écrou Par de apriete recomendado coppia di spunto consigliata
M2.5	1.5 Nm
M3	1 Nm
M4	2 Nm
M5, M14	3 Nm
M6	6 Nm
Mutter, Screw nut, écrou, Tuerca, dado, M20x1,5	8 Nm

Standard (no IP67)	F _r max.	F _a max.
24C, 30A, 36C/K/S, 40A/K/S, 58K	80 N	50 N
36A 6 mm, 1/4"	80 N	50 N
36A 8 mm	50 N	50 N
36J	300 N	300 N
50B	120 N	70 N
50V, 53S, 53V	20 N	10 N
58A	125 N	70 N
58B,N,T	220 N	120 N
WDG58D	400 N	400 N
WDGI58D	500 N	500 N
63B/Q, 67Q	220 N	120 N
70B	200 N	150 N
115T/M, 58C	200 N	120 N
58S, 58V	100 N	100 N



F_r max.
F_a max.



L<Lmax: 100 m, 150 m

Schirm, Shield, Blindage, Malla, Schermo

Vcc
GND

WDG...

L1/L2/L3:
K1/K2/K3:
Sx:

Erdschleifen vermeiden, Avoid ground loops, Eviter les boucles de masse, Evitar bucles de tierra, Evitare loop di massa

Frühwarnausgang
Early-warning output
Sortie d'alerte
Salida de advertencia prematura
uscita di preavvertimento

Schaltung
Circuit
Couplage
Conmutación
collegamento

G24, I24,
G05, I05,
524

IRLED
IRLED

high
low

01.04.2025 Angaben ohne Gewähr, Irrtümer und Änderungen vorbehalten. Information not warranted. Errors and modifications reserved. Spécifications sous réserve d'erreur. Sauf erreur ou omission. Indicaciones sin garantía. Se reserva el derecho de error y modificación. Indicazioni senza garanzia. Salvo errori e modifiche. Artikelnummer, Item number, Numéro d'article, Número de artículo: BAWDGMV00_32

